

## Heli Accessories 選購配件



### ACE RC T3AC Balance Charger for Li-Po Battery

### T3AC平衡功能鋰電池專用充電器 # 2536



The ACE RC T3AC BALANCE CHARGER is specifically designed for charging 2-cell and 3-cell Li-Po battery packs. The compact-size charger features built-in switch adaptor for input power source and individual cell balancing function for safe charging.

ACE RC T3AC是2至3片式鋰電池專用充電器，具備高安全性之分壓充電及平衡功能，並內建變壓轉換，迷你體積中的強大的功能絕非其他市售充電產品可比擬！

#### Specification 基本規格：

規格摘要	規格
Power supply voltage 母電源電壓	110-240V AC
Cell count range 適用電池片數	2-3cells
Max. charge current 最大充電電流	3×650mA
Dimension approx 尺寸	100×60×35mm
Weight approx 重量	180g



Connect to 2-Cell Li-Po Battery  
連接 2-Cell 鋰電池(7.4V)

Connect to 3-Cell Li-Po Battery  
連接 3-Cell 鋰電池(11.1V)

#### Charger LED Status 充電器LED狀態說明：

Operational mode display 使用狀態顯示方式	via 3 LEDs
Power on 開啓電源時	Orange (1 second) / 橘燈（停留1秒）
Stand By 待機狀態	Green / 綠燈
Charging 充電中	Red / 紅燈
Full 完成充電	Green / 綠燈
Fault 失敗	Flashing / 快閃燈號

#### Caution 注意事項：

1. ONLY for 2-cell & 3-cell Li-Po battery.
2. Proceed with charging in a safe environment.
3. DO NOT charge while the battery is still warm.
4. DO NOT charge an expanded or damaged battery.
5. Keep the charger away from humidity.
1. 限用於2或3片式鋰電池組。
2. 請於安全環境中進行充電。
3. 電池仍處於發熱狀態時，請勿充電。
4. 電池發生膨脹或受損，請勿充電。
5. 請勿於潮溼環境中使用。